

DIRECT VOLTAGE TRANSFORMER JIVD 50



JIVD50 is designed for direct measuring as PCB mounted type. These VTs offer an optional transformation between input and output voltage. Input is available from 300V - 600V and output is from 100mV – 7V by customer needs. These VTs are the best solution for high accurate measuring of voltage.

SPECIFICATION

Series	MAIN SPECIFICATION(Primary current type : Secondary current type)					
	Input Voltage(V)	Output Voltage	Excitation Current	Accuracy	Class	Mounting
JIVD50	300/380/500/600V	100mV~7V	≤0.5mA	50Hz to 400Hz	0.1 Class	PCB

DIMENSION & CIRCUIT

